

Model: KR3P-360-15**Input Data**

AC-Input Voltage	AC 380-500V (3-Phase)
DC-Input Voltage	540-710
Power Factor	0.45
External Input Fuse Recommendation	5A
Peak Turn on Current	30A max.

Output Data

Nominal Voltage	15Vdc
Output Current Range	24-21A
Output Current	24A at 15V
Output Power	360W
Power Reserves	20% Power Boost

Overview

Operate. Temperature Range	-25°C ... +60°C
Derating	3W/° at >+60°C
Efficiency, typ.	88.4 - 90%
Power Losses, typ.	41.76W
Mounting	Panel / Din rail
Dimension	182 x 104 x 60mm

Protections

Input Transient	2KV (MOV Based 550VAC)
Output Short Circuit	Short-circuit Protected
Output Over Load	Above 24A